RealScan-G10i

Proven and Powerful 10-Print Live Scanner.

User Manual

REV01



[RealScan-G10i-REV01-250618-EN]

Introduction

RealScan-G10i is an FBI Appendix F-certified FAP60 live scanner.

Powered by Xperix's cutting-edge optical and biometric technologies, it delivers high-resolution fingerprint images quickly and accurately, regardless of fingerprint conditions.

Additionally, RealScan-G10i features Xperix's proprietary fingerprint recognition algorithm, which accurately detects spoof fingerprints made from materials such as clay, rubber, silicone, adhesive, paper, and film.

It is a complete live scan solution optimized for a wide range of applications including national ID enrollment.

Important Notice

Information in this document is provided in connection with Xperix products. No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted by this document. Except as provided in Xperix's Terms and Conditions of Sale for such products, Xperix assumes no liability whatsoever, and Xperix disclaims any express or implied warranty, relating to sale and/or use of Xperix products including liability or warranties relating to fitness for a particular purpose, merchantability, or infringement of any patent, copyright or other intellectual property right. Xperix products are not intended for use in medical, life saving, life sustaining applications, or other applications in which the failure of the Xperix product could create a situation where personal injury or death may occur. Should Buyer purchase or use Xperix products for any such unintended or unauthorized application, Buyer shall indemnify and hold Xperix and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Xperix was negligent regarding the design or manufacture of the part.
Xperix reserves the right to make changes to specifications and product descriptions at any time without notice to improve reliability, function, or design.
Designers must not rely on the absence or characteristics of any features or instructions marked "reserved" or "undefined." Xperix reserves these for future definition and shall have no responsibility whatsoever for conflicts or incompatibilities arising from future changes to them.
Contact your local Xperix sales office or your distributor to obtain the latest specifications and before placing your product order.
Copyright © 2025 Xperix Inc.

*Third-party brands and names are the property of their respective owners

For inquiries, please contact us at: https://www.xperix.com/
201 Songpa-daero, Songpa-gu, Seoul, Korea, Terra Tower 2, Building A, 3rd Floor, Suite 305-308
Tel: +82 1588-8817, Fax: +82-2-881-5126

Disclaimer

1. Restrictions of Use

This passport reader must be used only for legal and authorized purposes. We are not responsible for any illegal activities or unauthorized usage.

2. Accuracy of information

The content of this manual is accurate as of the date of writing. Although the passport reader is designed to read the provided information as accurately as possible, the accuracy of the information cannot be guaranteed due to data input errors, technical issues, or other external factors. We are not responsible for any damage or loss resulting from these inaccuracies. The information in this manual is subject to change without notice due to product improvements.

3. Technical Support

This product must be installed and maintained according to the technical support provided by the manufacturer. We are not responsible for any damage or loss resulting from unauthorized repairs, modifications, or alterations.

4. Interference and Malfunction

This device may generate, use, and radiate radio frequency energy, and if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. We are not responsible for any interference or malfunction occurring in specific environments.

5. Legal Compliance

This product is designed to comply with various international and domestic regulations. Users are responsible for complying with local laws and regulations, and we are not responsible for any issues arising from non-compliance with legal requirements.

6. Liability

We are not liable for any direct, indirect, incidental, special, or consequential damages arising from the use of this product. This includes, but is not limited to, loss of profits, loss of data, inability to use the product, or other economic losses.

Copyright © 2025 Xperix Inc.

Copyright

© 2025 Xperix Inc. All rights reserved

All content and drawings in this manual, as well as the design, software, and technical data of this product, are the intellectual property of Xperix Inc. Unauthorized use, reproduction, distribution, modification, or transmission of this manual, this product, or any part thereof without the prior written consent of Xperix Inc. is strictly prohibited and may be subject to penalties under international copyright law and other applicable laws.

The name Xperix Inc. and other trademarks are registered trademarks of Xperix Inc. This copyright notice applies to all products and documents of Xperix Inc.

This manual provides reliable information, but we accept no liability for any loss caused by typographical errors. The information in this manual is subject to change without notice due to product improvements.

Safety Instructions

Please read the following instructions carefully before using this product. This information is crucial to ensure user safety and prevent damage to the user's property.



Failure to follow these instructions may result in serious injury or death.

Installation Instructions

Do not install the product in direct sunlight or in locations with high humidity or dust.

• This can cause fire or electric shock.

Install the product in a dry location.

• Moisture can cause product damage or electric shock.

Do not install the product near heat sources such as electric heaters.

• Overheating can cause fire or electric shock.

Install the product in a location free from electromagnetic interference.

• This can cause product damage or electric shock.

Install and repair the product through a qualified professional.

• Failure to do so may result in fire, electric shock, or injury.

• If the product is damaged due to unauthorized installation or disassembly by the user, repair costs will be charged.

Operation Instructions

Take care not to spill liquids such as water, beverages, or chemicals into the product.

• This can cause fire, electric shock, or product damage.

Copyright © 2025 Xperix Inc.

CAUTION Non-compliance may cause minor injury or product damage.

Installation Instructions

Protect the power cord from damage by foot traffic or pinching.

- This can cause product damage or injury.

Keep the product away from strong magnetic objects such as magnets, TVs, monitors (especially CRT monitors), and speakers.

- This can cause product malfunction.

Operation Instructions

Do not drop the product or subject it to impact or collision during use.

- This can cause product malfunction.

Do not press the product's buttons with excessive force or use sharp tools.

- This can cause malfunction.

Copyright © 2025 Xperix Inc.

Revision History

Version	Change	Date
REV01	Initial creation of the User Guide	2025-06-18

Copyright © 2025 Xperix Inc.

Table of Contents

System Requirements 9

RealScan-G10i 9

Components 10

Product Labeling 11

External View (Diagram) 12

External View 13

SDK Installation Guide 14

Device Driver Installation Guide 17

Sample APP(Example) Usage Guide 20

Trouble Shooting Guide 35

- The device does not power on 35
- Dirty errors occur continuously. 35
- The device powers on but does not scan. 35

Specifications 36

Regulatory Information 37

Copyright © 2025 Xperix Inc.

System Requirements

Before installing the SDK, please ensure the following.

• A device with the following specifications:

  - OS: Windows 7 or higher, Linux Ubuntu, Debian, Fedora, OpenSUSE, CentOS 32/64bit, Android 5.0 or higher

• This scanner must be used in an environment that supports USB 2.0 or higher to ensure stable data transmission.If a USB hub is used, it must provide sufficient power. In cases where the power supply is unstable or disconnected, please connect the scanner directly to a USB port on the main PC.

RealScan-G10i Unpacking Procedure

Before unboxing the RealScan-G10i, please check the list below.

• Remove the contents from the box and separate the components from the packaging material.

• Verify that all parts have been received. If any parts are missing, contact Xperix service.

• Check the product for damage. If the product is damaged, contact Xperix Service.

Copyright © 2025 Xperix Inc.

Components


To use the product at its best performance, please use only the USB cable and power adapter provided.

Using any cable or adapter may result in reduced performance or damage to the product. Failure to follow these precautions will void the warranty.

Item	Quantity	Image
RealScan-G10i	1EA	
PE-BAG + Screw 2ea (M2xL7) + PORT COVER UPPER	1EA	
USB Cable	1EA	
WIPER	1EA	


Copyright © 2025 Xperix Inc.


Product Labeling







External View (Diagram)










External View



Name	Description
Scan Area	Used for placing fingers to capture fingerprint images.
Power LED	Indicates whether power is being supplied to the device.
Navigation LED	Displays the currently active capture mode.
Preset Button	Allows the user to assign a predefined command to the button, which is executed immediately when pressed.


Copyright © 2025 Xperix Inc.

SDK Installation Guide

This page provides instructions for installing the SDK. Please follow the guide below to proceed with the installation.

1. **Run the file RealScan SDK_for_Windows_Installer_v2.x.x.xxx.exe.**


2. **SDK Introduction Screen.**



➔ Click the [Next] button.


Copyright © 2025 Xperix Inc.

3. License Agreement



➔ Click the [I Agree] button.


4. Choose Installation Location



➔ Click the [Install] button.

Copyright © 2025 Xperix Inc.

5. **Installation Successful**



➔ Click the [Finish] button.

Copyright © 2025 Xperix Inc.


Device Driver Installation Guide

This page provides instructions for installing the device driver. Please follow the guide below to proceed with the installation.


Note:

If the driver is installed while the device is connected to the PC via USB cable, the installation may not complete successfully. Ensure that the USB cable is disconnected from the PC before proceeding with the driver installation.

1. **Navigate to the Driver folder located at \Program Files\Xperix\RealScanSDK .**




2. **Run the file RealSeries_Driver_v3.1.1.1.exe.**




Copyright © 2025 Xperix Inc.

3. Driver Introduction Screen



➔ Click the [Next] button.

4. Installation Successful




➔ Click the [Finish] button.

Copyright © 2025 Xperix Inc.

5. After installation, you need to check in Device Manager to see if the device driver is installed properly.

Press the Windows key + R to open the Run dialog, type devmgmt.msc, and click OK. If the device is installed correctly, it will appear under 'Universal Serial Bus devices as RealScan-G10i.




Copyright © 2025 Xperix Inc.


Sample APP(Example) User Guide

This page provides instructions on how to use the Sample APP. Please follow the guide below to utilize the Sample APP.


1. Navigate to the BIN folder located at \Program Files\Xperix\RealScanSDK.



2. Move to the folder corresponding to your PC specifications.




3. Run the program RealScanExample_VC.exe




Copyright © 2025 Xperix Inc.


4. Click the Init SDK button




5. Click the Init Device button



6. Configure the capture mode.




7. Click the Start button and place your finger on the scanner.




Copyright © 2025 Xperix Inc.

8. Once the finger is placed, the fingerprint will be captured successfully.



Copyright © 2025 Xperix Inc.


9. Review the components of the Sample Application.



Device Connection Section

Item	Function
Init SDK	Initializes the SDK.
Init Device	Initializes the device and obtains the device handle.
Exit Device	Releases the device and associated resources.


Copyright © 2025 Xperix Inc.



Capture Settings Section

Item	Function
Mode	Sets the capture mode.
Auto	Enables automatic capture using a callback function.
Start	Starts fingerprint scanning.
Stop	Stops fingerprint scanning.
Take Manual	Allows manual capture after disabling the Auto checkbox.
Take Auto	Automatically invokes the configured callback function.
Custom Capt. Size	Configures the capture coordinates and image size.


Copyright © 2025 Xperix Inc.



Preview Section

Item	Function
Preview	Displays the captured image in the preview area.
No Draw	Does not display the captured image in the preview area.
Direct Draw	Directly displays the captured image in the preview area.
Callback	The image received via callback is displayed in the preview area.
Adv Callback	Displays the guide image and score along with the captured image.


Copyright © 2025 Xperix Inc.



Overlay Section

Item	Function
Type	Sets the type of overlay to be displayed in the preview area.
Color	Sets the color of the selected overlay type in the preview area.
Draw	Displays the configured overlay type and color in the preview area.
Clear All	Removes all overlays displayed in the preview area.


Copyright © 2025 Xperix Inc.



Device Section

Item	Function
Device	Displays device information.
Self-Test	Checks the device's illumination and contamination (dirty) status.
Check CustomID	Checks the custom ID of the device.
Calibrate	Checks for contamination on the surface of the scan area.
Heater Information	Not supported on RealScan-G10i.
View Software License	Displays the software license.


Copyright © 2025 Xperix Inc.



Overlay Section

Item	Function
Text	Displays text in the preview area.
Cross	Displays a cross marker in the preview area.
Line	Displays a line in the preview area.
Quadrangle	Displays a quadrangle in the preview area.
Hide All	Hides all overlays in the preview area.
Show All	Shows all overlays in the preview area.
Clear All	Resets all overlay settings.


Copyright © 2025 Xperix Inc.



IO Section

Item	Function
Key	Assigns a callback function to the preset button.
Mode LED	Configures the navigation LED.
Finger LED	Configures the finger navigation LED.
Status LED	Not supported on RealScan-G10i.
Beep	Plays a beep sound.
Wav	Plays an audio file.
LCD	Not supported on RealScan-G10i.


Copyright © 2025 Xperix Inc.



Option Section

Item	Function
Roll Capture Options	Configures detailed options for roll capture.
LFD Level	Sets the LFD (Live Finger Detection) level.
Other Capture Options	Configures additional options related to fingerprint capture.

Copyright © 2025 Xperix Inc.



Callback Option Section

Item	Function
Segmentation Options	Sets the actual number of segmented fingers and related information.
Custom Size	Configures the image size for segmented output.
Capture Options	Sets the capture orientation.

Trouble Shooting Guide

This document provides instructions on how to handle errors that frequently occur while using the product.

If you need any further technical support, please visit, please visit https://tech.xperix.com to create a new ticket and share your inquiry.

If you would like to learn more about error handling methods,

please visit https://tech.xperix.com/en/support/solutions and refer to the FAQ section.

Symptoms	Causes	Solutions
The device does not power on.	This may occur when the device is not properly connected.	Check the USB cable connection. Try connecting the device to a different USB port on the PC.
Dirty errors occur continuously.	Triggered when the surface of the scan area is contaminated.	Clean the surface of the scan area using a soft cloth.
The device powers on but does not scan.	This may occur when the device is not properly connected to the SDK.	Reinstall the device driver.

Copyright © 2025 Xperix Inc.

Specifications

Dimensions (WxLxH)	152 mm x 152 mm x 127 mm
Sensing Area (WxL)	81.28 mm x 76.2mm
Weight	1.8 kg
Resolution (DPI)	500DPI
Capture Mode	Flat (Four/Two/Single) and Rolled(Single) fingers
Image Size (WxL)	Four finger slap: 1600 x 1500 pixels Single flat / roll: 800 x 750 pixels
Supported Image Formats	RAW, BMP, WSQ, JPEG2000, ISO19794-4
Suface Protection	Optic Glass (Scratch free)
Ingress Protection	IP54
User Feedback Elements	Speaker, LED Indicator
Operating Temperature	-10 ℃ ~ 55 ℃ (-50 ℉ ~ 131 ℉)
Operating Humidity	10% ~ 90%
Power Source USB Voltage Level	USB Host 5.0V ±10%
OS	Windows 7 or higher 32/64bit Linux Ubuntu, Debian, Fedora, OpenSUSE, CentOS 32/64bit Android 5.0 or higher
FBI / Image Certifications	Identification Flats(Appendix F & Appendix P), Live-Scan (Tenprint) System(Appendix F), Live-Scan (Palm) System(Appendix P), without membrane
Certification	FBI, CE, FCC, KC, RoHS, USB-IF, UL, WHQL, BIS, IEC62471, STQC, WEEE, REACH

Copyright © 2025 Xperix Inc.

Regulatory Information

FCC Compliance Information

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) This device may not cause harmful interference.
(2) This device must accept any interference received, including interference that may cause undesired operation.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy, and if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
• Reorient or relocate the receiving antenna.
• Increase the separation between the equipment and receiver.
• Connect the equipment to an outlet on a circuit different from that to which the receiver is connected.
• Ask an operator or a skilled technician for assistance.
Unauthorized modifications or changes not expressly approved by the manufacturer could void the user's authority to operate the equipment under FCC regulations..

European Union CE Mark and Compliance Declaration

This product is CE marked in accordance with the R&TTE Directive (1999/5/EC). Xperix Inc. declares that this product complies with the essential requirements and other relevant provisions of Directive 1999/5/EC.
This device is a Class 1 radio equipment under the European Radio and Telecommunications Terminal Equipment (R&TTE) Directive (1999/5/EC)..

CE

Copyright © 2025 Xperix Inc.

WEEE Mark and Compliance Information

This product must be disposed of and recycled in accordance with the WEEE Directive (2012/19/EU). Xperix Inc. declares that this product complies with the mandatory requirements of the WEEE Directive and other relevant regulations. Users must return this product to appropriate recycling facilities, separating it from general waste, in accordance with local and national regulations.



Copyright © 2025 Xperix Inc.

©2025 Xperix Inc. The Xperix name and product names and numbers mentioned here are trademarks of Xperix Inc. All other trademarks and product names are trademarks or registered trademarks of their respective companies. The appearance, production status, and/or specifications of the product are subject to change without notice.

[RealScan-G10i-REV01-250618-EN]